# BIL 717 Image Processing Apr. 29, 2015

### **Graphical Models**

Erkut Erdem Hacettepe University Computer Vision Lab (HUCVL)

# **Energy Minimization**

• Many vision tasks are naturally posed as energy minimization problems on a rectangular grid of pixels:

 $E(u) = E_{data}(u) + E_{smoothness}(u)$ 

- The data term *E*<sub>data</sub>(*u*) expresses our goal that the optimal model *u* be consistent with the measurements.
- The smoothness energy *E*<sub>smoothness</sub>(*u*) is derived from our prior knowledge about plausible solutions.
- Recall Mumford-Shah functional

D. J. Fleet


K. Grauman

# Sample Vision Tasks


- **Image Denoising:** Given a noisy image  $\hat{l}(x, y)$ , where some measurements may be missing, recover the original image l(x, y), which is typically assumed to be smooth.
- Image Segmentation: Assign labels to pixels in an image, e.g., to segment foreground from background.
- Stereo matching
- Surface Reconstruction
- ...

# Smoothing out cluster assignments


• Assigning a cluster label per pixel may yield outliers:





original



• How to ensure they are spatially smooth?







#### Denoising as a Probabilistic Inference Perform maximum a posteriori (MAP) estimation by maximizing the *a posteriori* distribution: p(true image | noisy image) = p(u | v)• By Bayes theorem: likelihood of noisy image image prior given true image $p(u \mid v) = \frac{p(v \mid u)p(u)}{p(u \mid v)}$ p(v)normalization term • If we take logarithm: $\log p(u \mid v) = \log p(v \mid u) + \log p(u) - \log p(v)$ MAP estimation corresponds to minimizing the encoding cost $E(u) = -\log p(v \mid u) - \log p(u)$

# Modeling the Likelihood

• We assume that the noise at one pixel is independent of the others.

 $p(v \mid u) = \prod_{i,j} p(v_{ij} \mid u_{ij})$ 

• We assume that the noise at each pixel is additive and Gaussian distributed:


$$p(v_{ij} \mid u_{ij}) = G_{\sigma}(v_{ij} - u_{ij})$$

• Thus, we can write the likelihood:

$$p(v \mid u) = \prod_{i,j} G_{\sigma}(v_{ij} - u_{ij})$$

# Modeling the Prior

- How do we model the prior distribution of true images?
- What does that even mean?
  - We want the prior to describe how probable it is (a-priori) to have a
    particular true image among the set of all possible images.



# Natural Images

• What distinguishes "natural" images from "fake" ones?



# Simple Observation

• Nearby pixels often have a similar intensity:




• But sometimes there are large intensity changes.

S. Roth

# MRF-based Image Denoising

• Let each pixel be a node in a graph  $\mathcal{G} = (\mathcal{V}, \mathcal{E})$  with 4-connected neighborhoods.



### Image Denoising

• The energy function is given by

$$E(u) = \sum_{i \in \mathcal{V}} D(u_i) + \sum_{(i,j) \in \mathcal{E}} V(u_i, u_j)$$

- Unary (clique) potentials D stem from the measurement model, penalizing the discrepancy between the data v and the solution u.
- Interaction (clique) potentials V provide a definition of smoothness, penalizing changes in  $u.\,{\rm between}$  pixels and their neighbors.

# Denoising as Inference

- **Goal:** Find the image u that minimizes E(u)
- Several options for MAP estimation process:
  - Gradient techniques
  - Gibbs sampling
  - Simulated annealing
  - Belief propagation
  - Graph cut
  - ...

### Quadratic Potentials in 1D

• Let v be the sum of a smooth 1D signal u and IID Gaussian noise e: where  $u = (u_1, ..., u_N)$ ,  $v = (v_1, ..., v_N)$ , and

 $e = (e_1, ..., e_N).$ 

• With Gaussian IID noise, the negative log likelihood provides a quadratic *data term*. If we let the *smoothness term* be quadratic as well, then up to a constant, the log posterior is

$$E(u) = \sum_{n=1}^{N} (u_n - v_n)^2 + \lambda \sum_{n=1}^{N-1} (u_{n+1} - u_n)^2$$

D. J. Fleet

### Quadratic Potentials in 1D

• To find the optimal  $u^*$ , we take derivatives of E(u) with respect to  $u_n$ :

$$\frac{\partial E(u)}{\partial u_n} = 2\left(u_n - v_n\right) + 2\lambda\left(-u_{n-1} + 2u_n - u_{n+1}\right)$$

and therefore the necessary condition for the critical point is

$$u_n + \lambda \left( -u_{n-1} + 2u_n - u_{n+1} \right) = v_n$$

• For endpoints we obtain different equations:  $u_1 + \lambda (u_2 - u_2) = v_2$ 

$$u_1 + \lambda (u_1 - u_2) = v_1$$
 N linear equations  
 $u_N + \lambda (u_N - u_{N-1}) = v_N$  in the N unknowns

D. J. Fleet

### Missing Measurements

• Suppose our measurements exist at a subset of positions, denoted *P*. Then we can write the energy function as

$$E(u) = \sum_{n \in P} (u_n - v_n)^2 + \lambda \sum_{\text{all } n} (u_{n+1} - u_n)^2$$

- At locations n where no measurement exists, we have:  $-u_{n-1} + 2u_n u_{n+1} = 0$
- The Jacobi update equation in this case becomes:

$$u_n^{(t+1)} = \begin{cases} \frac{1}{1+2\lambda} (v_n + \lambda u_{n-1}^{(t)} + \lambda u_{n+1}^{(t)}) & \text{for } n \in P , \\ \frac{1}{2} (u_{n-1}^{(t)} + u_{n+1}^{(t)}) & \text{otherwise} \\ & & \text{D. J. Fleet} \end{cases}$$

### 2D Image Smoothing

• For 2D images, the analogous energy we want to minimize becomes:

$$\begin{split} E(u) &= \sum_{n,m \in P} (u[n,m] - v[n,m])^2 \\ &+ \lambda \sum_{\text{all}\,n,m} (u[n+1,m] - u[n,m])^2 + (u[n,m+1] - u[n,m])^2 \end{split}$$

where  $\boldsymbol{P}$  is a subset of pixels where the measurements  $\boldsymbol{v}$  are available.

#### Looks familiar??

### **Robust Potentials**

- Quadratic potentials are not robust to *outliers* and hence they over-smooth edges. These effects will propagate throughout the graph.
- Instead of quadratic potentials, we could use a robust error function *ρ*:

$$E(u) = \sum_{n=1}^{N} \rho(u_n - v_n, \sigma_d) + \lambda \sum_{n=1}^{N-1} \rho(u_{n+1} - u_n, \sigma_s),$$

D. J. Fleet

where  $\sigma_d$  and  $\sigma_s$  are scale parameters.


### **Robust Potentials**

• Example: the Lorentzian error function

$$\rho(z,\sigma) = \log\left(1 + \frac{1}{2}\left(\frac{z}{\sigma}\right)^2\right), \quad \rho'(z,\sigma) = \frac{2z}{2\sigma^2 + z^2}.$$

Error function


1



D. J. Fleet

### **Robust Potentials**

- Example: the Lorentzian error function
- Smoothing a noisy step edge



# Robust Image Smoothing

• A Lorentzian smoothness potential encourages an approximately piecewise constant result:






Original image

Output of robust smoothing

# Robust Image Smoothing

• A Lorentzian smoothness potential encourages an approximately piecewise constant result:



Original image




D. J. Fleet

### Image Segmentation

- Given an image, partition it into meaningful regions or segments.
- Approaches
  - Variational segmentation models
  - Clustering-based approaches (K-means, Mean Shift)
  - Graph-theoretic formulations
- MRF-based techniques

MRFs and Graph-cut

### Markov Random Fields



# $Energy(\mathbf{y};\boldsymbol{\theta},data) = \sum_{i} \psi_{1}(y_{i};\boldsymbol{\theta},data) + \sum_{i,j \in edges} \psi_{2}(y_{i},y_{j};\boldsymbol{\theta},data)$


#### D. Hoiem


# Solving MRFs with graph cuts


#### Main idea:


- Construct a graph such that every *st*-cut corresponds to a joint assignment to the variables **y**
- The cost of the cut should be equal to the energy of the assignment, E(y; data)\*.
- The minimum-cut then corresponds to the minimum energy assignment,  $y^* = \operatorname{argmin}_{v} E(y; \text{ data}).$


\* Requires non-negative energies












































#### De-noising with Field-of-Experts Modeling the Potentials [Roth and Black '05, Ishikawa '09] • Could the potentials (image priors) be learned from natural $E(X) = \sum (z_i - x_i)^2 / 2\sigma^2 + \sum \sum \alpha_k (1 + 0.5(J_k x_c)^2)$ images? Unary FoE prior likelihood Field of Experts x<sub>c</sub> set of nxn patches (here 2x2) (FoE), S. Roth & J<sub>k</sub> set of filters: 83 M. J. Black, CVPR 2005 non-convex optimization problem How to handle continuous labels in discrete MRF? From [Ishikawa PAMI '09, Roth et al '05] C. Rother

#### De-noising with Field-of-Experts [Roth and Black '05, Ishikawa '09]





original image

denoised using gradient ascent

PSNR 22.49dB SSIM 0.528

PSNR 27.60dB SSIM 0.810

• Very sharp discontinuities. No blurring across boundaries.

σ=20

• Noise is removed quite well nonetheless.

S. Roth